


Current Transducer LAC 300-S/SP10

For the electronic measurement of currents: DC, AC, pulsed..., with galvanic separation between the primary circuit and the secondary circuit.



$$I_{PN} = 300 \text{ A}$$



Electrical data

I_{PN}	Primary nominal RMS current	300	A
I_P	Primary nominal < 30 s	400	A
I_{PM}	Primary current, measuring range @ 85 °C	0 ... ±910	A
R_M	Measuring resistance @ $T_A = 85 \text{ °C}$ with ±24 V @ ±910 A _{max}	$R_{M \min}$ $R_{M \max}$ 0 20	Ω
I_{SN}	Secondary nominal RMS current	60	mA
N_P/N_S	Turns ratio	1 : 5000	
U_C	Supply voltage (±5 %)	±24	V
I_C	Current consumption	25+ I_S	mA

Accuracy - Dynamic performance data

ε	Error @ I_{PN} , $T_A = 25 \text{ °C}$	±1.4	%
ε_L	Linearity error	< 0.1	%
I_O	Offset current @ $I_P = 0$, $T_A = 25 \text{ °C}$	Typ	Max
I_{OM}	Magnetic offset current @ $I_P = 0$ and specified R_M , after an overload of $3 \times I_{PN}$		±0.15
I_{OT}	Temperature variation of I_O -40 °C ... +85 °C	±0.2	±0.50
t_{D90}	Delay time ¹⁾ to 90 % of I_{PN}	< 1	μs
BW	Frequency bandwidth (-3 dB)	DC ... 50	kHz

General data

T_A	Ambient operating temperature	-40 ... +85	°C
T_S	Ambient storage temperature	-45 ... +90	°C
R_S	Resistance of secondary winding @ $T_A = 85 \text{ °C}$	101	Ω
m	Mass	175	g
	Standards	EN 50155: 2001 UL 508: 2010	

Note: ¹⁾ For a $di/dt = 50 \text{ A}/\mu\text{s}$.

Features

- Closed loop (compensated) current transducer using the Hall effect
- Insulating plastic case recognized according to UL 94-V0.

Special features

- $I_{PN} = 300 \text{ A}$
- $I_P = 400 \text{ A}$ (< 30 s)
- $I_{PM} = 0 \dots \pm 910 \text{ A}$
- $N_P/N_S = 1 : 5000$
- $U_C = \pm 24 \text{ V}$ (±5 %)
- NEXANS FLAMEX 20 cable.

Advantages

- Excellent accuracy
- Very good linearity
- Low temperature drift
- Optimized response time
- Wide frequency bandwidth
- No insertion losses
- High immunity to external interference
- Current overload capability.

Applications

- Single or three phases inverters
- Propulsion and braking choppers
- Propulsion converters
- Auxiliary converters
- Battery chargers.

Application Domain

- Traction.

Current Transducer LAC 300-S/SP10

Insulation coordination

U_d	RMS voltage for AC insulation test, 50 Hz, 1 min	5.5 Min	kV
d_{Cp}	Creepage distance	23.7	mm
d_{Cl}	Clearance	14	mm
CTI	Comparative tracking index (group I)	600	

Safety



This transducer must be used in electric/electronic equipment with respect to applicable standards and safety requirements in accordance with the manufacturer's operating instructions.



Caution, risk of electrical shock

When operating the transducer, certain parts of the module can carry hazardous voltage (eg. primary busbar, power supply).

Ignoring this warning can lead to injury and/or cause serious damage.

This transducer is a build-in device, whose conducting parts must be inaccessible after installation.

A protective housing or additional shield could be used.

Main supply must be able to be disconnected.

